9651 HARD WIRED SECURITY SYSTEM



The Scantronic 9651 is a fully programmable 8 zone security panel, designed to offer maximum flexibility and ease of use. It is ideal for domestic installations as it offers exceptional value for money.

The 9651 has simple ABCD setting options, offering full and part-set options. Up to 4 keypads can be added to the system, allowing easy operation from any location in the home using 4 digit codes. With the addition of a scanprox module to the keypad, the 9651 can be easily set and unset using a proximity tag without the need to remember the access code.

The system can be connected to a speech dialler or plug-by communicator via a wire-in communications output. In addition, the system allows for flexibility in configuration, as it has three fully programmable outputs.

The 9651 has a 250 event log, which is date and time stamped to comply with ABI (Association of British Insurers) requirements.







9651 HARD WIRED SECURITY SYSTEM

TECHNICAL SPECIFICATION

Zones

Zone Attributes

Panel Keypads

Proximity Reader

Display
Level Setting
Event Log
Compliance
Keyswitch
Codes

Outputs Battery

System Power Supply
Aux DC Power for Detectors

Dimensions

Weight
Temperature Range
Communications Outputs

Scantronic Compatible Equipment:

8 fully programmable (CC, 2 wire with global tamper or 2 wire FSL)

Each zone can be programmed as one of the following types – personal attack, fire, normal alarm, final exit, 24 hour, entry route, not used, shock analyser (zones 1-4 only), technical alarm, key-switch (fixed & momentary options) attributes of chime, soak test, double knock, omit allowed

9651 blank metal end station and 9930EUR-50 LCD keypad packaged as a kit

Accepts a maximum of four 9930EUR-50 LCD keypads

An optional plug-on module that turns a Scantronic keypad into a combined keypad and proximity reader - compatible with a 9930EUR-50 keypad

Full feature LCD display with plain text up to 16 characters

A = Full Set, B, C & D = Part Set

250 event log with date and time stamped

Currently BS4737

Key-switch zone, full = A, part = B setting/unsetting, disarm and reset

 16×4 digit user access codes, 1 duress code, 1 engineer code

3 fully programmable outputs, 13.8v dc +/- 1%dc 1A total current output supply

Stand by battery 7Ah lead acid

Regulated at 1 Amp

500mA @ 13.7v dc

Control panel (H x W x D) = $240 \times 240 \times 90 \text{mm}$,

keypad (H x W x D) 120 x 170 x 27mm

Control panel = 3.15kg, keypad = 260g

-10°c to +55°c

8 outputs for any type of wire-in communications device such as a speech dialler, plug-by communicator etc.

934EUR-50 ScanProx module and tag

9930EUR-50 LCD keypad

420 Digital PIR Detector

430 Digital PIR Detector (pet tolerant)

440 Commercial Quad Detector

450 Ceiling-mounted Twintec Detector

460 Domestic Twintec Detector

480 Commercial Twintec Detector

Compatible with the speech dialler range

Scantronic is a leading brand of Cooper Security Ltd., part of Cooper Industries, employing over 28,000 people at more than 100 manufacturing sites around the world.

Scantronic manufactures security equipment for all types of commercial and domestic premises. The range is comprehensive, offering every type of solution from multizone hard-wired and wirefree systems, to detectors and social alarms. Installers trust us to deliver cost-effective products with the highest quality of field and support services to ensure you receive the best and most reliable systems, to secure you and your premises.

Dealer Details

Scantronic is a brand of Cooper Security Ltd.



